



THE UNIVERSITY *of* EDINBURGH

Edinburgh Research Explorer

An approximate gradient for fast nonlinear inversion of the EIT model

Citation for published version:

Polydorides, N, Ouyornkochagorn, T & McCann, H 2015, An approximate gradient for fast nonlinear inversion of the EIT model. in *16th International Conference on Biomedical Applications of Electrical Impedance Tomography*. <https://zenodo.org/record/17752/files/EIT2015_Proceedings.pdf>

Link:

[Link to publication record in Edinburgh Research Explorer](#)

Document Version:

Peer reviewed version

Published In:

16th International Conference on Biomedical Applications of Electrical Impedance Tomography

General rights

Copyright for the publications made accessible via the Edinburgh Research Explorer is retained by the author(s) and / or other copyright owners and it is a condition of accessing these publications that users recognise and abide by the legal requirements associated with these rights.

Take down policy

The University of Edinburgh has made every reasonable effort to ensure that Edinburgh Research Explorer content complies with UK legislation. If you believe that the public display of this file breaches copyright please contact openaccess@ed.ac.uk providing details, and we will remove access to the work immediately and investigate your claim.



An approximate gradient for fast nonlinear inversion of the EIT model

Nick Polydorides¹, Taweechai Ouypornkochagorn¹, Hugh McCann¹

¹School of Engineering, University of Edinburgh, UK. n.polydorides@ed.ac.uk

Abstract: We propose a methodology for speeding up the computation of a nonlinear inverse solution, by approximating efficiently the Jacobian of the forward model. This has practical advantages not only in linearising the inverse problem but also in computing the regularised solution.

1 Introduction

We consider the inverse problem of estimating a conductivity function $\sigma \in X$ from a finite set of electrical potential measurements $y \in \mathfrak{R}^m$ from the nonlinear model

$$y = F(\sigma) + n, \quad (1)$$

where n is additive random noise, $F : X \rightarrow \mathfrak{R}^m$ is an analytic forward mapping, with continuous first and second weak derivatives and X is the space of bounded positive functions spanning over a closed domain Ω . For a choice of regularisation term $R : X \rightarrow \mathfrak{R}$, the inverse problem is to estimate

$$\hat{\sigma} = \arg \min_{\sigma \in X} \{ \|F(\sigma) - y\|^2 + R(\sigma) \}. \quad (2)$$

Using a gradient-based algorithm, such as the Gauss-Newton, a local minimum can be traced iteratively for $n = 0, 1, \dots$

$$\sigma_{n+1} = \sigma_n + h_n \quad (3)$$

$$h_n = \arg \min \{ \|DF_{\sigma_n}(h) - \delta y_n\|^2 + R(h) \}, \quad (4)$$

where DF_{σ_n} is the Fréchet derivative of F at a feasible $\sigma_n \in X$, and $\delta y_n = y_n - F(\sigma_n)$. The need for fast image reconstruction in EIT has been addressed in the past, and methods like single-step inexact Newton-based regularised reconstructions [1], [2] have been popular in this context, and to a lesser extent Newton-Kantorovich algorithms Broyden methods [3].

2 Approximate gradient method

Let $|\Omega|$ denote the volume of the domain to be imaged, then consider the weighted mean conductivity value

$$\bar{\sigma} = \frac{1}{|\Omega|} \int_{\Omega} dx \sigma(x) w(x), \quad \text{where} \quad \int_{\Omega} dx w(x) = 1. \quad (5)$$

As any $\sigma \in X$ admits a decomposition $\sigma = \bar{\sigma} + p$, then we claim that

$$DF_{\sigma}(h) \approx DF_{\bar{\sigma}}(h) = \frac{1}{\bar{\sigma}^2} DF_1(h), \quad (6)$$

where $\mathbf{1}(x)$ is the unit conductivity function in Ω . Options for the weights may include

$$w(x) \propto \mathbf{1}(x) \quad \text{or} \quad w(x) \propto \sum_{i=1}^d |\sigma(x) \nabla u_i(x)|, \quad (7)$$

with $u_i(x) = F(\sigma)$ denoting the forward solution for the i th boundary current. By the analyticity of F we have

$$DF_{\sigma} = DF_{\bar{\sigma}} + \frac{1}{2} D^2 F_{\bar{\sigma}} p + o(p^2), \quad (8)$$

and thus to first-order accuracy

$$\|DF_{\sigma} - DF_{\bar{\sigma}}\| \leq \frac{1}{2} \|D^2 F_{\bar{\sigma}}\| \|p\|, \quad (9)$$

and we can replace DF_{σ_n} in the Gauss-Newton iteration with $DF_{\bar{\sigma}_n}$, such that at each iteration we obtain the approximate Jacobian by scaling accordingly a precomputed Jacobian DF_1 . To see the computational advantage of this scheme let $\mathbf{J}_1 = \sum_{i=1}^m u_i s_i v_i'$ the Jacobian matrix at discrete model with $k > m$ elements and unit conductivity, and $R(h) = \lambda \|h\|^2$, then the iterative solution is given by

$$\sigma_{n+1} = \sigma_n + \sum_{i=1}^m \gamma_i^n v_i, \quad \text{for } \gamma_i^n = \langle u_i, \delta y_n \rangle \left(\frac{s_i \bar{\sigma}_n^2}{s_i^2 + \lambda \bar{\sigma}_n^4} \right) \quad (10)$$

3 Simulations

We implement the approximate gradient scheme using a regularised Gauss-Newton algorithm and compare convergence and timings against the respective implementation involving the exact Jacobian. These tests were based on simulations performed with EIDORS 3D [3] using a model with 8640 elements and 208 measurements, with a targeted oscillatory conductivity function $0.01 \leq \sigma(x) \leq 110$. The timings for 6 iterations on a macbook pro running Matlab were 114 s and 8 s for the exact and approximate schemes respectively, while the errors in data and image are those appearing in fig. 1.




Figure 1: Numerical comparison of the Gauss-Newton method with exact and approximate gradients using $w(x) \propto \mathbf{1}(x)$.

4 Conclusions

The numerical results suggest that the compromise in the convergence of the nonlinear solver due to the approximate Jacobian is very small compared to the profound computational savings.

References

- [1] Lechleiter A., Rieder A., Newton regularizations for impedance tomography: convergence by local injectivity, *Inverse Problems*, 24, 065009, 2008.
- [2] Cheney M., Isaacson D., Newell J. C., Goble J., Simske S., Noser: an algorithm for solving the inverse conductivity problem. *Internat. J. Imaging Systems and Technology*, 2, 66-75, 1990.
- [3] Holder D. S. (ed) *Electrical Impedance Tomography: Methods, history and applications*, IoP, 2002.